

SAMSUNG BUSINESS

Guide to Updating LFD Firmware from a MagicInfo Server

1. Go to the **DEVICE** tab on the server portal. Click the link on the left that says **SOFTWARE UPDATE**.
2. Choose **REGISTER AND PUBLISH**. Click the button at the top that says **REGISTER**. Select the Player type from the drop down. Select the Model of the display from the next drop down. For the software name, enter a name that helps you know which version you are working with; for example, the version number of the firmware. Next to file name, click the magnifying glass, and navigate to the firmware file archive that has been downloaded and select it. It should be in .zip format, and the file name should end with _BEM.

Register Software

Device Type: SPLAYER

Device Model Name: PH43F

Software Name: 2050.2

File Name: PMF_PMF-BC_PHF_MLF_Pt

OK Cancel

Click OK, and the firmware file will be uploaded to the server.

3. Next, we will push the firmware to the displays. Back on the register and publish screen, you will now see the firmware listed. Check next to the firmware and click **PUBLISH** at the top.

Register Edit Delete Publish Download Export

<input type="checkbox"/>	Device Model Name	Software Name	Version
<input checked="" type="checkbox"/>	PH43F	2050.2	T-HKMLAKUC 2050.2

SAMSUNG BUSINESS

The server will then display this screen:

Publish [X]

Device Type	SPLAYER
Device Model Name	PH43F
Software Name	2050.2
Software File Name	swuimage.bem
Software Version	T-HKMLAKUC 2050.2
CRC Info.	abb519bd

Publish time: Publish Now Schedule Publish

Schedule Publish: 2018-06-20 [calendar icon] 00:00 [time icon]

Applied Version: VERSION_ALL [dropdown arrow]

Select Applicable Device(s): By Device Model By Device Group

[Empty box for selecting device groups]

[Publish] [Cancel]

Under **SELECT APPLICABLE DEVICE(S)**, select **BY DEVICE GROUP**. Select the groups that you wish to send the firmware to. Note that if you send it to a model that does not support that firmware, it will ignore it.

When you click **PUBLISH**, it will begin sending the firmware to the display. When the display finishes downloading and installing, it will shut off, and then come back on with the latest firmware running.