The following guide is intended to walk a user through copying content from a USB drive, and configuring the LFD's onboard S3 Player for local playback according to a user defined schedule. You will require the IR remote control, and a USB flash drive with your content loaded onto it.

STEP 1: Copy Content from USB to the LFD

- 1. Insert the USB flash drive into the USB port of the LFD.
- 2. Power on the LFD.
- 3. Press the **HOME** button on the IR remote. The Home Menu will be displayed.

MagicInfo Player S3			
Playe	P F iety of content, such as I channels, templates or files.	Schedule	Template
Clone Product	D Settings	🗱 Video Wall	Network Status
Picture Mode	On/Off Timer	A Ticker	🔅 More settings

4. Use the left/right arrow keys and enter on the IR remote to select the **PLAYER** menu option. The Player Menu will be displayed.



5. Using the left/right/up/down arrow keys and enter on the IR remote to highlight and select the **OPTIONS** menu option in the upper right corner. The Options Menu will be displayed.



6. Use the up/down arrow keys on the IR remote to select the **SEND** menu option. The Send Menu screen will be displayed.



7. Using the arrow keys on the IR remote, highlight the **SELECT ALL** menu option in the upper right corner, and press enter on the IR remote to select it.



8. Check marks will appear in the upper left of the icons representing the content files from your USB flash drive. We will be copying all of them onto the onboard storage in the LFD itself, so the USB flash drive may be removed. Using the arrow keys on the IR remote, highlight the **SEND** menu option. Press enter on the IR remote to select it.



9. Using the arrow keys and enter key on the IR remote, highlight and select the **SEND** menu option. The menu will ask you to confirm that you are copying to the internal memory of the LFD. Press the enter key on the IR remote to select the **INTERNAL** option from the menu.



10. The Send menu will display, confirming the details of the operation. Using the arrow keys and enter key on the IR remote, highlight the **START** menu option and select it.

	V	<i>k</i> 6				
	Send				10	
	Item(s) selected from USB sto	orage: 3	Tot	al Size: 0.16 N	1B	
	Destination: Internal			05 GB Availab	ole a g	
My Templates		itart	Cancel			
	هان 🖂 آفت					
System Volume Inform	Test Image 3.jpg					

11. The LFD will transfer the content files from the USB flash drive onto the internal storage of the LFD, displaying a status bar dialog showing progress. The LFD will confirm that all the files were successfully sent. Press the enter key on the IR remote to accept the **OK** menu option and close the menu.

Network File	Successfully sent. Total (3/3)	= USB	>>> 🗾 Inte	ernal		
	Test Image 3.jpg			100%		
My Templates		OK				
	Test Image 3				/8- ЛС	
System Volume Info	rm Test Image 3.jpg					

12. The screen will now show two copies of your content, the original on the USB flash drive, and the copy placed into internal memory. You may now remove the USB flash drive.



STEP 2: Create Schedule on LFD

13. Press HOME on the IR remote to bring up the Home menu.

Player	seredule	Template	
Clone Product	🗖 ID Settings	Video Wall	Network Status
Picture Mode	On/Off Timer	A Ticker	Dore settings

14. Using the left/right arrow keys and the enter key, highlight the **SCHEDULE** menu option and select it. This will bring up the Schedule menu.

Schedule			🖌 Type : Local 🔽 Device	: Internal Options
Playing Time	[CH1]Channel 1	[CH2]Channel 2	[CH3]Channel 3	and the second s
		Schedule your content on		The default content wi
	+ Add Program			be played when there is no program scheduled.

15. Using the up/down/left/right arrow keys and enter key to highlight the **ADD PROGRAM** menu option in center of the screen, and press enter to select it. This will display the schedule creation menu.

Schedule Channel	1			×
Add content to create a prog				
Start Time	12:00 am	Stop Time	09:00 am	📃 All Day
Channel Name	Channel 1			
		Save Cancel		

16. Using the arrow keys and the enter key on the IR remote, highlight and select the plus icon, labeled "Add content to create a program on the channel" in the middle left. This will display the Open File menu. Your content files will now be shown.

Schedule Cha	e a program on the channel.			X
Open File		Device : Internal	Content : All	Sort by : File Name
My Templates	Test Image 2 Test Image 2.jpg			
Test image 1	Test Image 3			
Test Image 1.jpg	Test Image 3.jpg	Done Cano	cel	

17. From the Open File screen, you can use the arrow keys and the enter key to place check marks next to all the content files you want to add to the schedule.

Open File	1 item(s) selected	Device : Internal	Content : All	Sort by : File Name
	Test Image 2			
My Templates	Test Image 2.jpg			
Set Image 1	Test Image 3			
Test Image 1.jp	Test Image 3.jpg			
		Done Cano	el	

18. Once your content has been selected, use the arrow keys and enter key to navigate to the **DONE** menu option at the bottom of the screen. This will return you to the Schedule creation menu. From this screen you have several options. You can configure the START TIME for your content, and the STOP TIME. You can select the check box next to ALL DAY if you want it to run 24 hours. Once you have set when you want your content to play, use the arrow and enter keys to navigate to and select the SAVE menu item at the bottom of the screen.

Schedule Channel	1			×
Add content to create a progr	am on the channel.			
Start Time	12:00 am	Stop Time	09:00 am	All Day
Channel Name	Channel 1			
		Save Cancel		

19. This will return you to the main Schedule Menu.

Playing Time	• [CH1]Channel 1	[CH2]Channel 2	[CH3]Channel 3	1
	Â			Test image 1
				- 10 million
		•		Program Info
	12:00 am ~ 09:00 am	Schedule your content or		12:00 am ~ 09:00 am
				Content :
				Test Image 1.jpg
05:30 am				
05:00 am 05:30 am 06:00 am				

20. Press **RETURN** on the IR remote control go return to the Home menu. Using the left/right arrow keys and the enter button on the IR remote, and highlight and select the **PLAYER** menu item.

Playe Play a vari scheduled	f ety of content, such as channels, templates or files.	Schedule	Template
Clone Product	D Settings	Video Wall	Network Status
Picture Mode	On/Off Timer	A Ticker	🔅 More settings

21. Using the arrow keys and enter key on the IR remote, highlight and select the LOCAL CHANNEL menu option. Your content will begin to play.

Player	V Device	Internal 🗸 Conte	ent : All 🛛 🔽 Sort	by : File Name Options	×
	t stored in the selected			21	7 item(s)
No channel.		Test Image 3			
Network Channel	My Templates	Test Image 3.jpg			
Channel	Test image 1	0/8- 0,10			
Local Channel	Test Image 1.jpg				
	Test Image 2				
Network File	Test Image 2.jpg				